
QR Code & Bluetooth, Prox Reader Model: QR500BLE



RFID card transmission formats, LED and

Application:

Buzzer control.

Schools, communities, office buildings, hotels, shopping malls, shops, public service places, etc.

Specification:

- Maximum Read Range*: 100mm
- Frequency:
 - ✓ ASK at 125KHz
 - ✓ CPU: 13.56MHz
- OSDP protocol: V2.17
- Multi Wiegand Output:
 - ✓ AWID: Up to 58bits
 - ✓ EM, 2308: W26/34
 - ✓ HID: WG26/27/34/35/37
 - ✓ KKID: WG34/50
 - ✓ Mifare: WG34
- Operating Voltage: 7-12VDC
- Operating Current: ≤100mA
- Standby Current:≤50mA
- Working Temperature: -30°C to 65°C
- Operating Humidity: 0 to 95%RH
- LED Control Input: Dry Contact, NO
- Buzzer Control Input: Dry Contact, NO
- Dimensions: 86(L) x 86(W)x 25(D)mm
- Weight: 150g





QR500BLE

Feature:

- Smooth attractive design, adapt to all-weather
- OSDP & Wiegand output: OSDP as default, Wiegand is an option.
- Dual color LED: Blue/Green.
- Green connector for wiring.
- Supports Multi Prox Cards:
 - ✓ AWID
 - ✓ EM, 2308
 - ✓ HID
 - √ KK: KK234, KK250
- Supports Multi Smart Cards:
 - ✓ Mifare
 - ✓ Mifare Sector
 - ✓ CPU, KK1208
- Built-in QR Code scanner
- Bluetooth technology, Shake smart phone to open the door
- Manufactured in KEYKING's ISO:9001 registered facility.